

ELECTRIC START INVERTER GENERATOR

6,500 STARTING WATTS

WITH 312CC ENGINE

DIGITAL DISPLAY ECO MODE LED FLOODLIGHT RETRACTABLE HANDLE



REMOTE START PARALLEL READY 2-WIRE AUTO START READY

COVERED OUTLETS (IP 66)


FLAT-FREE WHEELS

GENERATOR SPECS

RUNNING WATTS	6,000
VOLTAGE	240V
AMPS	25A
DECIBEL	68(Dba)

PLUG TYPES

AC 240V 15A AC 240V 15A



DC 12V 8A



INCLUDES



ENGINE OIL



OIL FUNNEL



SCREWDRIVER



RAIN COVER



2-WIRE AUTO START CABLE



BATTERY CHARGER



USB A & C ADAPTER

MODEL # 123 Gi65E

BAR CODE # 9346472100017